



Keeloq® rolling-code remote control systems

Receiver programming instructions for the Challenger Mk III when using ET-BLUE

To master erase:

- Power down
- Short both the "RX L" and the "RX B" pins to the middle pin. (use your flat screw driver to do this)
- While keeping the short in place power-up.
- The LED will begin to flash.
- After +/- 15 sec the LED will go off.
- Power down and remove short.
- Power up again after +/- 5 sec.
- LED will come back on.
- All transmitters will be erased.

Programming a transmitter for open close operation:

- While pressing and hold the required button on your transmitter,
- Short "RX B" to the middle pin
- When LED flashes remove short.
- Repeat the above for additional transmitters. Up to 10 transmitters can be programmed for this operation.

Programming a transmitter for light on/off and holiday lock out operation:

- While pressing and hold the required button on your transmitter,
- Short "RX L" to the middle pin
- When LED flashes remove short.
- Repeat the above for additional transmitters. Up to 5 transmitters can be programmed for this operation.

If any transmitter has been incorrectly learnt into either of the inputs, then master erase and start learning all transmitters again.